CORRIGENDA

Operating Instructions contain misdescription. Please refer to the following for the correction.

11.5 Configure the settings relating to the camera operations [Cam. Function] [Extra optical zoom]

Wrong	Right
[Extra optical zoom]	[HD Extra optical zoom]
Select the extra optical zoom setting from the	Select the <u>HD Extra</u> optical zoom setting from the
following.	following.
• On (Max X90): Images can be zoomed in on with the	On (Max X45): Images can be zoomed in on with the
optical zoom (1x - 30x) and the extra optical zoom	optical zoom (1x - 30x) and the <u>HD Extra</u> optical zoom
(higher zoom factors, up to <u>90</u> x).	(higher zoom factors, up to <u>45</u> x).
Off (Max X30): Does not use the extra optical zoom.	Off (Max X30): Does not use the HD Extra optical zoom.
• Default : On (Max X <u>90</u>)	• Default : On (Max X <u>45</u>)
About extra optical zoom	About <u>HD Extra</u> optical zoom
Among approx. 2.07 megapixel image capture area of	Among approx. 2.07 megapixel image capture area of
the MOS image sensor, the central part of approx. <u>0.23</u>	the MOS image sensor, the central part of approx. <u>0.92</u>
megapixels is extracted for shooting. That enables the	megapixels is extracted for shooting. That enables the
shooting with a higher zooming effect. When the image	shooting with a higher zooming effect. When the image

capture size of <u>1280x720</u> or less is applied, the zoom

factor can be adjusted up to 45x.

[Digital zoom]

factor can be adjusted up to 90x.

capture size of 640x360 or less is applied, the zoom

Wrong	Right
 [Digital zoom] Select the digital zoom setting from the following. On (Max X1080): Images can be zoomed in on with the optical zoom (1x - 30x), extra optical zoom (up to 90x) and the electronic zoom (higher zoom factors, up to 1080x). Off: Does not use the digital zoom. 	 [Digital zoom] Select the digital zoom setting from the following. On (Max X1080): Images can be zoomed in on with the optical zoom (1x - 30x), HD Extra optical zoom (up to 45x) and the electronic zoom (higher zoom factors, up to 1080x). Off: Does not use the digital zoom.
 Default: Off Note When "On (Max X1080)" is selected, digital zooming will stop when the zoom factor has reached 90x. When the zoom factor is 90x or more, the setting of the preset positions will become unavailable. 	 Default: Off Note When "On (Max X1080)" is selected, digital zooming will stop when the zoom factor has reached 45x. When the zoom factor is 45x or more, the setting of the preset positions will become unavailable.

11.6.3 Configure the settings relating to the preset positions ("Preset position" setup menu) IMPORTANT

Wrong	Right
 When the zoom factor is <u>90</u>x or more, the setting of the	 When the zoom factor is <u>45</u>x or more, the setting of the
preset positions will become unavailable.	preset positions will become unavailable.

11.6.4 Configure the settings relating to the auto pan function("Auto pan" setup menu) [Speed] Note

Wrong	Right
Even when the selected zoom factor is higher than <u>90</u> x, the camera will start panning with <u>90</u> x zoom factor.	 Even when the selected zoom factor is higher than <u>45</u>x, the camera will start panning with <u>45</u>x zoom factor.