## **Panasonic**

# Super Dynamic Weather Resistant HD Network Camera WV-SW316L WV-SW316



### HD / 1,280 x 960 H.264 Network Camera featuring Super Dynamic

#### **Key Features**

- 720p HD images up to 30 fps
- Newly developed 1.3 Megapixel high sensitivity MOS Sensor
- Multiple H.264 (High profile) streams and JPEG streams ensure simultaneous real time monitoring and high resolution recording by "UniPhier®", Panasonic's proprietary System LSI platform.
- Full frame (Up to 30 fps) transmission at 1,280 x 960 image size
- Super Dynamic and ABS (Adaptive Black Stretch) technologies deliver 128x wider dynamic range compared to conventional cameras.
- Face Super Dynamic technology ensures clear face image.
- H.264 and MPEG-4 are selectable for system migration.
- High sensitivity with Day/Night (IR) function:
   WV-SW316L: 0.3 lx (Color), 0 lx (B/W) at F1.3 (Wide) when the IR LED is lit
   WV-SW316: 0.3 lx (Color), 0.05 lx (B/W) at F1.3 (Wide)
- Motorized varifocal lens equipped:
   The zoom ratio can be changed and adjusted to an optional photographic area through the operation buttons on this unit and the setup menu.
- IR LED equipped: The equipped infrared LED makes it possible to take pictures at zero lx.(WV-SW316L)
- VIQS (Variable Image Quality on Specified area) technology allows the designated area to retain higher image quality while the excluded area will have a decreased image quality, which enables to use lower image file size and bit rate.
- ABF (Auto Back Focus) ensures easy installation.
- Digital Noise Reduction: 3D-DNR ensures noise reduction in various conditions.
- Electronic sensitivity enhancement: Auto (Up to 16x) / OFF
- Up to 6.4x Extra Optical Zoom at VGA resolution.
   3.1-10 mm, 3.2x vari-focal auto iris lens (3.1-20 mm (equivalent),
   6.4x with Extra Optical Zoom (at VGA))
- VMD (Video Motion Detector) with 4 programmable detection areas,
   15 steps sensitivity level and 10 steps detection size
- Privacy Zone can mask up to 2 private areas, such as house windows and entrances/exits.
- Alarm sources including 1 terminal input, VMD and Panasonic alarm command can trigger actions such as SDHC/SD memory recording, FTP image transfer, E-mail notification, Indication on browser, Alarm terminal output, and Panasonic protocol output.
- Full duplex bi-directional audio allows interactive communication between camera site and monitoring site.

- JPEG image compression ratio can be changed by alarm so that higher quality image can be provided.
- Prioritized stream control: One of the video streams can be prioritized when multiple recorders or client PCs are accessing the camera so that the recorder or the client PC can maintain the frame rate.
- SDHC/SD Memory card slot for manual recording (H.264 / JPEG), alarm recording (H.264 / JPEG) and backup upon network failure (JPEG)
- H.264/MPEG-4 max. bit rate/client and Total bit rate control allows flexible network traffic management. Frame rate priority mode controls bit rate and compression ratio to provide the specified frame rate.
- Multi-language: English / Italian / French / German / Spanish / Russian / Chinese / Japanese
- IPv4/IPv6 protocol supported
- Supports SSL, DDNS (viewnetcam, RFC2136)
- Still images (JPEG) can be viewed on mobile phones via Internet.
- Onvif compliant model
- Analog Monitor output for easier installation
- IP66 rated water and dust resistant. Compatible with IEC60529 measurement standard.
- Dehumidification device for use in various weather conditions
- Fog compensation function equipped as standard.

#### **Standard Accessories**

• Installation Guide	• Code Label*21 pc.
The following is used during installation proc  4 P alarm cable	Adapter box
*1 The CD-ROM contains the operating instructions (HTN	

#### **Specifications**

TV System	Image C		NTSC PAL	
Camera	Image Senso		1/3 type MOS Sensor	
	Effective Pixe		Approx. 1.3 megapixels	
	Scanning Mo		Progressive scan 4.80 mm (H) x 3.60 mm (V) (3/16"(H) x 5/32"(V))	
	Scanning Are Minimum Illu		W-SW316L: Color: 0.3 lx, B/W: 0 lx at F1.3 (Shutter: 1/30 s, AGC: High, when the IR LED is lit	
	IVIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIII	mination		
			Color: 0.019 lx, at F1.3 (Shutter: 16/30 s, AGC: High)	
			WV-SW316: Color: 0.3 lx, B/W: 0.05 lx at F1.3 (Shutter: 1/30 s, AGC: High),	
	ID LED Light		Color: 0.019 lx, B/W: 0.003 lx at F1.3 (Shutter: 16/30 s, AGC: High)	
	IR LED Light IR LED irradiation distance		WV-SW316L: Off/Auto(High/Mid/Low)	
			WV-SW316L: 15 m {49.21 feet}	
	White Balanc		AWC (2,000 ~ 10,000 K), ATW1 (2,700 ~ 6,000 K), ATW2 (2,000 ~ 6,000 K)	
	Light Control	Mode	Outdoor: Automatic integration of ALC and ELC	
			Indoor [50 Hz]: Automatic integration of ALC and ELC (up to 1/100 s)	
			Indoor [60 Hz]: Automatic integration of ALC and ELC (up to 1/120 s)	
	Shutter Spee	d	Fix shutter: 1/30, 3/100, 3/120, 2/100, 2/120, 1/100, 1/120,	
			1/250,1/500, 1/1,000, 1/2,000, 1/4,000, 1/10,000 (only at Super-Dynamic Off	
	Super Dynami		ON / OFF	
	Face Super Dy	/namic	ON / OFF (Only at Super Dynamic: ON)	
	Adaptive Black Stretch		ON / OFF (Only at Super Dynamic: OFF)	
	AGC		ON (LOW, MID, HIGH) / OFF	
	Electronic Sensitivity UP		OFF / AUTO (Max. 2x (2/30 s), 4x (4/30 s), 6x (6/30 s), 10x (10/30 s), 16x (16/30 s)	
	Day & Night	(IR)	Mode: AUTO1 / AUTO2 / ON / OFF, Level: High / Low, with external control	
	Dynamic Range		52 dB typ. (Super Dynamic: On, Light control mode: indoor scene)	
	Digital Noise Reduction		High / Low	
	Video Motion Detection		4 areas, Sensitivity: 15 steps, Detection size: 10 steps	
	Privacy Zone		Up to 2 zones, Gray	
	VIQS		ON / OFF	
	Camera Title	(OSD)	Up to 20 characters (alphanumeric characters, marks)	
	Focus Adjustment		ABF / MANUAL	
Lens	Focal Length		3.1 mm ~ 10 mm, 3.2x (3.1-20 mm (equivalent), 6.4x with Extra Optical Zoom (at VGA))	
	Angular Field of View		H: 27.9° (TELE) ~ 90.6° (WIDE), V: 20.9° (TELE) ~ 66.9° (WIDE)	
	Maximum Aperture Ratio		1:1.3 (WIDE) ~ 1:3.0 (TELE)	
	Focusing Ra		0.3 m ~ ∞	
Adjusting A		90	Horizontal: ±100° (Camera mount bracket)	
jusuily F	gic		Vertical: ±100° (Camera mount bracket)	
Browser CIII	Camera Con	trol	Brightness, AUX ON / OFF	
onse: uUI	Display Mod		Spot, Quad: Image from 16 cameras can be displayed in 4 different Quad	
	Display Mode		screens or 16 split screen (JPEG only). 20 characters camera title available.	
	Digital Zoom		1x, 2x, 4x controlled by browser GUI	
	Digital Zoom		Up to 20 alphanumeric characters	
	Camera Title Clock Display		Time: 12H/24H, Date: 5 formats on the browser, Summer time (Manual)	
	Alarm Contro		Reset	
	One Shot Capture		A still picture will be displayed on a newly opened window.	
	Audio		Mic (Line) Input: ON / OFF Volume adjustment: Low / Middle / High,	
	00.11		Audio Output: ON / OFF Volume adjustment: Low / Middle / High	
	SD Memory Data Download		Still or motion Images recorded in the SDHC/SD memory	
			card can be downloaded.	
	GUI/Setup Me	nu Language	English, French, Italian, Spanish, German, Russian, Chinese, Japanese	
	System Log		Up to 100 (Internal), Up to 4,000 (SDHC/SD memory when	
			therecording format is set to JPEG.) error logs	
	Supported O	S*1*2	Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows Vista®	
	l		Microsoft® Windows® XP SP3	
	Supported B	rowser	Windows® Internet Explorer® 10.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit)	
			Windows® Internet Explorer® 8.0 (32 bit), Windows® Internet Explorer® 7.0 (32 bit).	
			Microsoft® Internet Explorer® 6.0 SP3	
Network	Network IF		10Base-T / 100Base-TX, RJ-45 connector	
	Image Resolution '4   Aspect ratio: [4 : 3]		H.264: 1,280 × 960 / VGA (640 × 480) / QVGA (320 × 240), up to 30 fp	
			MPEG-4: VGA (640 × 480) / QVGA (320 × 240), up to 30 fps	
			JPEG (M-JPEG): 1,280 × 960 / VGA (640 × 480) / QVGA (320 × 240), up to 30 fps	
		Aspect ratio: [16:9]*3	H.264: 1,280 × 720 / 640 × 360 / 320 × 180, up to 30 fps	
			JPEG (M-JPEG): 1,280 × 720 / 640 × 360 / 320 × 180, up to 30 fps	
	H.264/MPEG-4 *5 *6	Transmission Mode	Constant bitrate / Framerate priority / Best effort / Advanced VBR	
			1/3/5/7.5/10/12/15/20/30 fps	
			64 / 128 / 256 / 384 / 512 / 768 / 1,024 / 1,536 / 2,048 / 3,072 /	
	1		4,096 / 8,192* kbps * H.264 mode only	
	1	Image Quality	LOW / NORMAL / FINE	
		Refresh Interval		
			UNICAST / MULTICAST	
	JPEG		10 steps	
	1		0.1 fps ~ 30 fps	
			PULL / PUSH	
	Audio Comp		G.726 (ADPCM) 32 kbps / 16 kbps, G.711 64 kbps	
	Audio Mode		OFF / Mic (Line) input / Audio output / Interactive (Half duplex) / Interactive (Full duplex)	
	Authentication	n for Audio	Level 1 only / Level 2 higher / All users	
	Total Bit Rate		64 / 128 / 256 / 384 / 512 / 768 / 1,024 / 2,048 / 4,096 / 8,192 kbps / Unlimited	
	Supported P		IPv6: TCP/IP, UDP/IP, HTTP, HTTPS, RTP, FTP, SMTP, DNS, NTP,SNMP, DHCPv6, MLD, ICMP, AR	
			IPv4: TCP/IP, UDP/IP, HTTP, HTTPS, RTSP, RTP, RTP/RTCP, FTP,SMTP, DHCP, DNS, DDNS, NTP,	
			SNMP, UPnP, IGMP, ICMP, ARP	
	FTP Client		Alarm image transmission, FTP periodic transmission (When the	
			FTP transmission is failed, backup on an optional SDHC/SD memory card is available.	
	No. of Simultaneous Users SDHC/SD Memory Card (Option)		Up to 14 users (Depends on network conditions)	
			H.264 recording: Manual REC / Alarm REC (Pre/Post) / Schedule REC	
			JPEG recording: Manual REC / Alarm REC (Post) / Backup upon network failure	
			Compatible SD (SDHC) card: Panasonic 256 MB, 512MB, 1 GB, 2 GB, 4 GB*, 8 GB*, 16 GB*, 32 GB* mode	
	1		*SDHC card	
	Cellular Phone Compatibility		JPEG image, AUX control (by access level)	
	Mobile Terminal Compatibility		iPad, iPhone, iPod touch (iOS 4.2.1 or later) Android™ mobile terminals	
Alarm			1 terminal input, VMD, Command alarm	
midIIII	Alarm Source			
	Alarm Actions		SDHC/SD memory recording, E-mail notification, Alarm terminal output,	
			Indication on browser, FTP image transfer, Panasonic protocol output	
	Alarm Log		With SDHC/SD memory card: 5,000 logs, without SDHC/SD memory card: 1,000 logs	
	Schedule		Alarm / VMD / Access permission / H.264 recording/ Forcible black & white mode(WV-SW316	
Input/ Output			VBS: 1.0 V [p-p]/75 Ω, NTSC composite, RCA Jack VBS: 1.0 V [p-p]/75 Ω,PAL composite, RCA Jack	
	Microphone/Line Input		MIC IN and Line IN are selectable. ø3.5 mm stereo mini jack	
			(monaural input) (Applicable microphone: Plug-in power type)	
	1			
			Supply voltage: 2.5 V ±0.5 V Input impedance: approx. 2 kΩ	
	Audio Outpu	t		
	Audio Outpu External I/O		Supply voltage: 2.5 V ±0.5 V Input impedance: approx. 2 kΩ e3.5 mm stereo mini jack (monaural output) Line level ALARM IN, DAY/NIGHT IN, ALARM OUT, AUX OUT	
General		Terminals	ø3.5 mm stereo mini jack (monaural output) Line level	

C-UL (CAN/CSA C22.2 No.60950-1),


DOC (ICES003 ClassA)

(EN55022 ClassB, EN55024)


TV System		NTSC	PAL	
General	Power Source and	12 V DC: 850 mA		
	Power Consumption	* FOR UL LISTED MODEL(S), ONLY CONNECT 12 V DC CLASS 2 POWER SUPPLY.		
		PoE (IEEE 802.3af compliant) 48 V: 200 mA (Class 0 device)		
	Ambient Operating Temperature	-40 °C ~ +50 °C (-40 °F ~ 122 °F)		
	Ambient Operating Humidity	90 % or less (without condensation)		
	Water and Dust Resistance	IP66, IEC60529 measuring standard compatible		
	Dimensions	94 mm (W) × 89 mm (H) × 226 mm (L)	(3-7/10" (W) × 3-1/2" (H) × 8-7/8" (L))	
	Mass (approx.)	1.4 kg (3.09 lbs.)		
	Finish	Main body: Aluminum die cast/resi	n, metallic silver coating	
		Front cover section clear part: Poly	carbonate resin	

- \*1 For further information about PC system requirements and precautions for when using Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows Vista®, or Windows Internet Explorer click "Manual"-"Open" from the supplied CD-ROM and refer to "Notes on Windows / Internet Explorer versions". For information on the camera models of the supported operating systems, refer to our website (http://security.panasonic.com/pss/security/).
- \*2 When using IPv6 for communication, use Microsoft® Windows® 8 or Microsoft® Windows® 7 or Microsoft® Windows Vista®.
- \*3 MPEG-4 is not supported.
- \*4 [4 : 3] and [16 : 9] are alternative. \*5 H.264 and MPEG-4 are alternative.
- \*6 Transmission for 2 streams can be individually set in the same compression method.
  \*7 For further information about compatible devices, refer to our website
- (http://security.panasonic.com/pss/security/support/info.html).

#### **Part Names and Functions**



#### **Appearance**



#### Trademarks and registered trademarks

- Iracemarks and registered trademarks

   Microsoft, and Windows are registered trademarks of Microsoft Corporation in the U.S. and other countries.

   iPad, iPhone and iPod touch are registered trademarks of Apple Inc.

   UniPhier is a registered trademark of Panasonic Corporation.

   "MEGA Super Dynamic", and "i-PRO SmartHD" logos are trademarks or registered trademarks of Panasonic Corporation.

   ONVIF and the ONVIF logo are trademarks of ONVIF Inc.

   All other trademarks identified herein are the property of their reposition of the control of the cont
- All other trademarks identified herein are the property of their respective owners.

- Pandand dadelinans identified neterinate the property of their respective owners.

   Important
   Safety Precaution: Carefully read the Important Information, Installation Guide and operating instructions before using this product.
   Panasonic cannot be responsible for the performance of the network and/or other manufacturers' products used on the network.
- Masses and dimensions are approximate.
- Specifications are subject to change without notice.

#### **DISTRIBUTED BY:**

