

12MP Sensor Indoor 360-degree Fisheye Network Camera

Panasonic WV-X4173 captures the highest quality images in even very challenging and dynamic environments. In particular, the image of the person's face or object at the edge of the fisheye is clear with less distortion.

Intelligent Auto (iA) monitors scene dynamics and motion to adjust key camera settings automatically in real-time reducing distortion such as motion blur on moving objects. Adopting H.265 Smart Coding technology, bandwidth efficiency is intelligently increased for longer recording and less storage. Cameras out-of-the-box, use an encryption module standardized by FIPS Publication 140-2 for secure video streaming.

Extreme image quality for evidence capturing under challenging conditions

- Clear and less distorted image of the person's face and objects at the edge of the fisheye
- Instant response to sudden light changes like tunnel entry and exit
- Auto Shutter speed control for fast moving objects

Extreme bandwidth compression with new Panasonic H.265 Smart Coding

- Longer recording and less storage space compared to any H.264 based compression techniques
- New self-learning ROI* encoding (Auto VIQS) dynamically detects motion areas to keep vehicles and humans in good picture quality while lowering your bandwidth *Region of Interest

Extreme Data Security

- Full encryption SD card edge recording to keep your data safe
- FIPS140-2 CAVP compliant *Using encryption module standardized by FIPS publication 140-2
- Full end-to-end system encryption with supported VMS and devices to protect from IP snooping/spoofing and detect data alteration

Complete with powerful analytics built-in

- Heat map: Visualization of people's traffic pattern and staying times
- People Counting: Statistics data on the number of people entering and leaving a specific zone
- MOR (Moving Object Remover): Monitoring of only the surrounding environment by removing people and other moving objects from video

Key Features

- 12MP Sensor
- 2992x2992 pixel fisheye image up to 30fps
- iA (intelligent Auto)
- H.265 Smart Coding
- i-VMD License Bundled
- Onvif Profile G / S / T

Industry examples

- Transportation (Airport / Subway station)
- Logistics / Factory
- Education / Hospital
- Retail / Bank
- Building







Specifications


Camera	ifications Image Sensor	Approx. 1/2 type 12MP CMOS image sensor
Camera	Minimum Illumination	
	Minimum Illumination	Color : 0.3 lx, BW : 0.2 lx
		(F1.9, Maximum shutter : Off (1/30 s), AGC : 11) Color : 0.02 lx, BW : 0.01 lx
	1.1.11	(F1.9, Maximum shutter : max. 16/30s, AGC : 11) *1
	Intelligent Auto	On / Off
	Maximum shutter	Max.16/30s to Max. 1/10000s
	Wide Dynamic Range*2	On / Off, The level can be set in the range of 0 to 31.
	Dynamic Range	Max.84 dB (Wide Dynamic Range : On, Level: 31)
	Image Settings	Gain (AGC), White balance
	Image Compensation	Adaptive black stretch, Back light compensation (BLC),
		Fog compensation, High light compensation (HLC),
		Digital noise reduction
	Day / Night (Electrical)	Off / Auto
	Video Motion Detection (VMD)	On / Off, 4 areas available
	Intelligent VMD (i-VMD)*3	Type 8 *Bundled License
	Privacy Zone	On / Off, Up to 8 zones available
	Camera Title (OSD)	On / Off, Up to 20 characters (alphanumeric characters, marks)
	Fixing angle adjustment	-5°, 0°, +5°
Lens	Zoom Ratio	1x
	Digital (electronic) zoom	Choose from 3 levels of x1, x2, x4
	Focal length	1.4 mm {1/16 inches}
	Maximum Aperture Ratio	1:1.9
	Focus range	0.5 m {19-11/16 inches} - ∞
	Angular Field of view	Horizontal: 183° Vertical: 183°
DORI	Distance to the object	Detect (25 ppm / 8 ppf) : 29.9 m / 98.2 ft
20	in the center of the image	Observe (62.5 ppm / 19 ppf) : 12.0 m / 39.3 ft
	In the center of the image	Recognize (125 ppm / 38 ppf): 6.0 m / 19.6 ft
		Identify (250 ppm / 76 ppf) : 3.0 m / 9.8 ft
	Coverage radius	Detect (25 ppm / 8 ppf) : 56.1 m /184.2 ft
	when mounted at a height	Observe (62.5 ppm / 19 ppf) : 20.6 m / 67.6 ft
	of 3 m (10 ft)	Recognize (125 ppm / 38 ppf): 8.4 m / 27.6 ft
	013111(1011)	Identify (250 ppm / 76 ppf) : 0.3 m / 0.9 ft
Browser	Camera Control	Brightness, AUX On / Off
GUI	Audio	Mic (Line) Input : On / Off Volume adjustment : Low / Middle / High
doi	Audio	
	GUI /	Audio Output : On / Off Volume adjustment : Low / Middle / High
		English, Italian, French, German, Spanish, Portuguese, Russian,
	Setup Menu Language	Chinese, Japanese
Network		10Base-T / 100Base-TX, RJ45 connector
	Resolution <ceiling></ceiling>	•Fisheye mode (max. 30 fps/25 fps)
	<wall></wall>	2992×2992 / 2192×2192 / 1280×1280 / 640×640 / 320×320
		Quad PTZ mode (max. 15 fps/12.5 fps), Single PTZ mode (max. 15 fps/12.5 fps)
		2560×1920°4 / 2048×1536 / 1600×1200 / 1280×960 / 800×600 / VGA / QVGA
	<ceiling></ceiling>	Double Panorama mode (max. 15 fps/12.5 fps)
		2560×1440 / 1920×1080 / 1280×720 / 640×360 / 320×180
		•Fisheye + Double Panorama mode (max. 15 fps/12.5 fps)
		(Fisheye) 2992×2992 / 2192×2192 / 1280×1280 / 640×640 / 320×320
		(Double Panorama) 1280×720 / 640×360 / 320×180
		•Fisheye + Quad PTZ mode (max. 15 fps/12.5 fps)
		(Fisheye) 2992×2992 / 2192×2192 / 1280×1280 / 640×640 / 320×320
		(Quad PTZ) 1280×960 / 800×600 / VGA / QVGA
		•Quad streams mode
		(Single PTZ (Quad streams)) 1280×960 / 800×600 / VGA / QVGA (max. 15 fps/12.5 fps)
		(Quad PTZ) 2560×1920 / 2048×1536 / 1600×1200 / 1280×960 /
		800×600 / VGA / QVGA (max. 5 fps)
	<wall></wall>	Panorama mode (max. 15 fps/12.5 fps)
	<vvali></vvali>	2560×1440 / 1920×1080 / 1280×720 / 640×360 / 320×180
		•Fisheye + Panorama mode (max. 15 fps/12.5 fps)
		Fisheye + Panorama mode (max. 15 fps/12.5 fps) (Fisheye) 2992×2992 / 2192×2192 / 1280×1280 / 640×640 / 320×320
		(Fishleye) 2332×2332 / 2132×2132 / 1260×1260 / 640×640 / 320×320
		(Panorama) 1280×720 / 640×360 / 320×180

Network	H.265/	Transmission Mode	Constant bit rate / VBR / Frame rate / Best effort
		Transmission Type	Unicast port (AUTO)/ Unicast port (MANUAL)/ Multicast
		Image Quality	10 steps
	Smart (GOP (Group of pictures) control :
			On (Frame rate control)* / On (Advanced)* / On (Mid) / On (Low) / Off
			*On (Frame rate control) and On (Advanced) are only available with H.265
			Auto VIQS : On / Off
			G.726 (ADPCM) : 16 kbps / 32 kbps
	Audio Compression		G.711 : 64 kbps
	Cupported Protocol		AAC-LC'6 : 64 kbps / 96 kbps / 128 kbps
	Supported Protocol Maximum concurrent access number		IPv6 : TCP/IP, UDP/IP, HTTP, HTTPS, SMTP, DNS, NTP,
			SNMP, DHCPv6, RTP, MLD, ICMP, ARP, IEEE 802.1X, DiffServ
			IPv4 : TCP/IP, UDP/IP, HTTP, HTTPS, RTSP, RTP, RTP/RTCP,
			SMTP, DHCP, DNS, DDNS, NTP, SNMP, UPnP, IGMP, ICMP,
			ARP, IEEE 802.1X, DiffServ
			Up to 14 users (Depends on network conditions)
		SDHC/SD	H.265 / H.264 recording :
	Memor	y Card (Option)	Manual REC / Alarm REC (Pre/Post) / Schedule REC
			JPEG recording :
			Manual REC / Alarm REC (Pre/Post)
		Compatible SDXC/SDHC/SD card :	
		Panasonic 2 GB, 4 GB*, 8 GB*, 16 GB*, 32 GB*, 64 GB**, 128 GB**,	
		256 GB**model	
			*SDHC card, ** SDXC card (except miniSD card and microSD card)
	Mobile 7	Terminal Compatibility	iPad, iPhone, Android™ terminals
	ONVIF	Profile	G/S/T
Alarm	Alarm S	Source	3 terminals input, VMD, Command alarm
	Alarm Actions	SDXC/SDHC/SD memory recording, E-mail notification,	
		HTTP alarm notification, Indication on browser,	
			Panasonic alarm protocol output
Input/	Monito	r output	VBS: 1.0 V [p-p] / 75 Ω, composite, ø3.5 mm mini jack
Output	(for adj	ustment)	An NTSC or PAL signal can be outputted from camera
	Audio Ir	put For microphone	ø3.5 mm stereo mini jack, Recommended applicable microphone : Plug-in power typ
			(Sensitivity of microphone : -48 dB ±3 dB (0 dB=1 V / Pa,1 kHz))
			Input impedance : Approx. 2 kΩ (unbalanced) Supply voltage : 2.5 V ±0.5 V
		For line	Input level : Approx. –10 dBV
	Built-in	microphone	Nondirectional electret condenser microphone
		Output*7	ø3.5 mm stereo mini jack (monaural output)
	, tadio (Juipui	Output impedance : Approx. 600 Ω (unbalanced) Output level : –20 dB'
	Evterns	al I/O Terminals	ALARM IN1 (Alarm input 1/ Auto time adjustment input) (x1)
	LXtorric	a i/O Terrimidis	ALARM IN2 (Alarm input 2/ ALARM OUT) (x1)
			ALARM IN3 (Alarm input 3/ AUX OUT) (x1)
General	Safoty		UL (UL60950-1), c-UL (CSA C22.2 No.60950-1), CE, IEC60950-1
General	EMC		FCC (Part15 ClassA), ICES003 ClassA, EN55032 ClassB, EN55024, EN5503
		Source and	
			DC power supply: DC 12 V 560 mA/Approx. 6.7 W
	Power	Consumption	PoE (IEEE802.3af compliant)
			Device : DC 48 V 150 mA/Approx. 7.2 W (Class 0 device)
		nt Operating	-10 °C to +50 °C (14 °F to 122 °F)
	Tempe		
	-	t Operating Humidity	10% to 90 % (no condensation)
	Dimens	sions	ø150 mm × 49.5 mm (H) {ø5-29/32 inches × 1-15/16 inches (H)}
	Mass (a	approx.)	Approx. 420 g {0.93 lbs}

'7 The audio output can be switched to the monitor output.

Refer to the Operating Instructions on the our support web site for descriptions of how to switch the output.

Appearance



² When "On (level 30 or 31)" is selected for "Wide Dynamic Range(WDR)", the frame rate is restricted to a maximum of 15fps (30fps mode) or 12.5fps (25fps mode).

3 Auto VIQS, i-VMD, can not be used at the same time.

4 When "Single PTZ" mode is used in wall installations, the 2560×1920 resolution cannot be used.

<sup>To Transmission for 2 streams can be individually set.

When recording audio on an SD memory card, only use AAC-LC (Advanced Audio Coding - Low Complexity).</sup>

Bundled License

Plug-in Software for i-VMD

i-VMD is possible to detect objects in the specified

area by advanced video analysis technology

i-VMD : People Counting, Heat-map, MOR (Moving Object Remover), Intruder Detection, Loitering Detection, Cross line Detection, Object Detection, Scene change Detection



Notification sent to the monitoring screen

Optional Accessories

■ Mount Bracket / Other







WV-OWI 500-W







•Brackets are available in four colors, Fine silver, Light gray, Gray and i-PRO white. It is possible to use them in different color combinations.

Trademarks and registered trademarks

- iPad and iPhone are trademarks of Apple Inc., registered in the U.S. and other countries.
 Android is a trademark of Google LLC.
- ONVIF is trademarks or registered trademarks of Onvif Inc.
 All other trademarks identified herein are the property of their respective owners.

- Safety Precautions : Carefully read the Basic Information, Installation Guide and
- Operating Instructions before using this product.

 Panasonic cannot be held responsible for the performance of the network and/or other manufacturers' products used on the network.
- Masses and dimensions are approximate. Specifications are subject to change without notice.

Panasonic

Panasonic Corporation

Panasonic i-PRO Sensing Solutions Co., Ltd.

https://ipro.panasonic.com https://security.panasonic.com https://www.linkedin.com/company/i-pro-sensing-solutions-co-ltd/ (2A-268BA)